7000 Watt Portable Generator

Perfect for jobsite activities and home backup power

PORTABLE GENERATOR

FEATURES & BENEFITS

ENGINE

- Honda GX390 13 HP* OHV gas engine
- Overhead valve (OHV) engine provides improved fuel efficiency, longer life, easier maintenance, and less noise
- Low oil shutdown protects engine by automatically turning it off when oil is low
- Cast iron sleeve on engine supplies extra protection from wear and tear

WATTAGE

- 7000 Running watts; 8750 Maximum watts

GAS TANK & RUN TIME

- 8 gallon gas tank with fuel gauge runs up to 10,4 hours @ 50% load

CONTROL PANEL

- (4) 120V outlets, (1) 120/240V twistlock outlet
- Circuit breaker protection

FEATURES

- Automatic Voltage Regulation (AVR) protects sensitive equipment and appliances from harmful voltage fluctuation
- CordKeepers™ hold cord securely in outlet

PORTABILITY

- 10” flat free wheels and dual folding handles for easy mobility

ACCESSORIES

- (2) 1 quart bottles of engine oil

WARRANTY

- 2 year limited warranty

POWERED by HONDA™

MODEL: PM0497000.02

MODEL SPECIFICATIONS

Running Watts:	7000
Max Watts:	8750
Engine Mfg/Type:	Honda GX390 13 HP* OHV
Gas Tank Size:	8 gallon
Run Time:	10,4 hours @ 50% load
Outlets:	(4) 120V 5-20R, (1) 120/240V L14-30R
Warranty:	2 year limited

Dimensions: 31.3” x 20.9” x 24.30” • Weight: 198 lbs. • UPC: 0-10163-49675-6

*AS RATED BY ENGINE MANUFACTURER

©2008 PRAMAC. ALL RIGHTS RESERVED.